

Designed to empower.



Fronius Primo GEN24

Product advantages

- 01 Integrated shade management
- D2 Backup power right from the start
- 03 Built-in longevity
- 04 Flexibility for greater potential
- 05 Sustainably future-proof

The heart of the photovoltaic system



01 Integrated shade management

Highest yields even in shade: That's what the Fronius GEN24 achieves with the Dynamic Peak Manager. The intelligent algorithm optimizes PV yields at the string level, eliminating the need for expensive module level optimization components.

02 Backup power right from the start

Harness backup power directly from the sun with the Fronius GEN24 equipped with PV Point. In the event of a power failure, energy is supplied via a designated socket with no need for a battery as long as the sun is shining.

03 Built-in longevity

The Active Cooling Technology effectively safeguards the electrical components, protecting them from heat development, therefore extending the service life of our inverters and securing the longevity of customers' investment.

04 Flexibility for greater potential

Thanks to the SuperFlex Design, the Fronius GEN24 is ideally equipped for complex roof situations. With the ability to align PV modules in different orientations and strings from 3 modules on, installers have the flexibility to design solar systems tailored to their customers' individual needs.


05 Sustainably future-proof


For those seeking a hybrid inverter solution, there's good news: Through an upcoming software upgrade, your device can be retrofitted with a battery connection, enabling the Full Backup power option so you have power even during a grid outage.


Impressive power data


The Fronius GEN24 impresses with maximum power at high temperatures.














Technical data

3.8/5.0/6.0 kW				Primo GEN24 208-240 & GEN24 208-240 Plus								
		3.8 5.0						6.0				
	Number of MPP trackers		2			2			2			
	Voltage withstand limit	VDC					600					
			208 V _{ac}	220 V _{ac}	240 V _{ac}	208 V _{ac}	220 V _{ac}	240 V _{ac}	208 V _{ac}	220 V _{ac}	240 V _{ac}	
	Rated input voltage (Udc,r)	V	360	380	400	360	380	400	360	380	400	
	Feed-in start voltage (U _{dc start})	V		80		80			80			
ata	Operating voltage range	V		65-480			65-480			65-480		
t d	MPP voltage range (at rated power)	V		200-480)		230-480			230-480)	
Input data			MPPT	MPPT1 MPPT2		MPPT	Γ1 N	1PPT2	MPPT	1 1	1PPT2	
Ä	Max. short circuit current per MPPT $(I_{sc})^{1}$	A	36		19	36		19	36		19	
	Number of DC connections ²		2		2	2		2	2		2	
			MPPT1	MPPT2	Total	MPPT1	MPPT2	Total	MPPT1	MPPT2	Total	
	Max. usable DC power	W	3,940	3,940	3,940	5,150	5,150	5,150	6,190	6,190	6,190	
	Max. PV generator output	Wpeak	5,700	5,700	5,700	7,500	6,800	7,500	8,000	6,800	9,000	
			208 V _{ac}	220 V _{ac}	240 V _{ac}	$208V_{\text{ac}}$	220 V _{ac}	240 V _{ac}	$208V_{\text{ac}}$	220 V _{ac}	240 V _{ac}	
	AC rated power (Pac,r)	W	3,800	3,800	3,800	5,000	5,000	5,000	5,740	6,000	6,000	
e a	Apparent power	VA	3,800	3,800	3,800	5,000	5,000	5,000	5,740	6,000	6,000	
Output data	Max. Output power	VA	3,800	3,800	3,800	5,000	5,000	5,000	5,740	6,000	6,000	
Ħ	Rated AC output current	А	18.3	17.3	15.8	24	22.7	20.8	27.6	27.3	25	
utp	Mains connection (U _{ac,r})	V		S	Single pha	se 208 V	/ 220 V	′ 240 V (-	12 / +109	%)		
ō	Frequency (frequency range fmin - fmax)	Hz			5	0 Hz / 60	Hz (45 F	Iz – 66 H	z)			
	Distortion factor	%					< 3.5					
	Adjustable power factor					8.0	- 1 ind. /	сар.				
			_									
ata it			120 V _{ac}									
it d	Rated Output power PV Point	VA	1,560									
Output data PV Point	Rated AC voltage PV Point	V			Sin	gle phase	120 V /	220 V / 2	40 V			
ō	Switching time	sec.					< 23					

The Fronius GEN24 can be upgraded to a Fronius GEN24 Plus hybrid inverter in the future through the UP.storage software upgrade. This upgrade activates battery functionality, enabling the possibility of a Full Backup power solution. However, external grid switching devices are required for this functionality. The technical specifications for battery operation and Full Backup operation are detailed below:

Full Backup power and battery function only available with GEN24 Plus			Primo GEN24 208-240 Plus								
			3.8		5.0		6.0				
data ;kup³			220 V _{ac}	240 V _{ac}	220 V _{ac}	240 V _{ac}	220 V _{ac}	240 V _{ac}			
t da acku	Rated Output power Full Backup	VA	3,800	3,800	5,000	5,000	6,000	6,000			
Output data Full Backup³	Mains connection Full Backup	V	1~NPE 220 V / 240 V								
9 🖫	Switching time	sec.	< 35								
_	Number of DC inputs		1								
tio	Max. Input current (Idc max)	А	22								
tte	DC input voltage range (Udc min - Udc max) 4	V	150-455								
Battery connection	Connection technology DC battery		1x DC+ and 1x DC- spring-type terminals for solid: copper AWG 12-8								
ပ	Max. Charging power with AC coupling 5	W	3,800 5,000 6,000								

¹ The combined I_{sc} of each string, multiplied by a factor of 1.25, must be less than or equal to the Isc of the respective MPPT.

² The maximum usable input current of the 3.8kW, 5.0kW, and 6.0kW is 22A for MPPT1 and 12A for MPPT2.

³ For Full Backup, additional external components are required for grid separation.

⁴ AC power derating of the inverter occurs with a DC battery input voltage of 419.7 V and higher.

⁵ Depending on the connected battery.

			Primo GEN24 208-240 & GEN24 208-240 Plus										
				3.8			5.0			6.0			
	Dimensions (height × width × depth)	inch/mm			20.4	+ x 18.7 x	6.5 / 518	3 x 474 x	164				
	Weight (inverter)	lbs./kg				35.56	lbs. / 15.	08 kg					
	Protection class						Type 4X						
	Protection class						1						
	Night consumption	W					<10						
	Overvoltage category (DC/AC) 6						2/4						
	Cooling					Active Co							
	Installation	05/00			Ind	door and			on				
	Ambient temperature range	°F/°C %				-40 to +	140 / -40 0-100) to +60					
ata	Permissible humidity Noise emissions	[%] dB (A)	0-100 < 42										
ğ I	Max. altitude	ft/m	< 42 13,123 / 4,000										
era		10/111		2x DC+1	2x DC+2				erminals	for solid:			
General data	Connection technology DC PV		2x DC+1, 2x DC+2 and 4x DC- spring-type terminals for solid: copper AWG 14-8										
	Connection technology AC		Spring-type terminals for solid: copper stranded / fine stranded: copper: AWG 14-8 Backup power spring-type terminals: AWG 16-8										
	Certificates and standard compliance		UL 1741 Third Edition (incl. UL1741 Supplement SA and SB), UL CRD - Non-Isolated EPS Interactive PV Inverters Rated Less Than 30kVA UL1998 (for functions: AFCI, RCMU, PVRSE and isolation monitoring), IEEE 1547:2018 incl. IEEE 1547a:2020, IEEE 1547.1:2020, IEEE 1547:2003 incl. IEEE 1547.1:2005 ANSI/IEEE C62.41, FCC Part 15 A & B, CSA C22. 2 No. 107.1-16 (reaffirmed 2021), CSA C22.2 No.290-19, CSA C22.2 No.330-23, CSA C22.3 No.9:20 UL1699B:2021										
	Country of manufacture						Austria						
>			208 V _{ac}	220 V _{ac}	240 V _{ac}	208 V _{ac}	220 V _{ac}	240 V _{ac}	208 V _{ac}	220 V _{ac}	240 V _{ac}		
ienc	Max. Efficiency	%	97.4	97.4	97.6	97.4	97.4	97.6	97.4	97.4	97.6		
Efficiency	CEC (ηCEC)	%	96.5	96.5	96.5	97	97	97	97	97	97		
ŭ	MPP adjustment efficiency	%					> 99.9						
			ı										
ve	DC insulation measurement					In	tegrated						
ecti	DC disconnector					In	tegrated						
Protective equipmen	Reverse polarity protection					In	tegrated						
пο	Arc Fault Circuit Interruption (Arc Guard)					In	tegrated						
(n	WLAN / 2 × Ethernet LAN		Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON)										
Interfaces	6 digital inputs			Connec	ction to ri	ipple con	trol rece	iver, ener	gy mana	gement			
erfa	6 digital inputs/outputs					In	itegrated						
Int	Emergency shutdown (WSD)					In	tegrated						
	Data logger and web server	Fronius Smart Meter WR / Modbus RTU (third-party)											

Technical data

7.7/10.0 kW Primo GEN24 208-240 & GEN24 208-240 Plus 10.0 7.7 Number of MPP trackers 2 Voltage withstand limit VDC 600 208 Vac 220 Vac 240 V_{ac} 208 V_{ac} 220 Vac 240 Vac V 365 385 365 365 385 Rated input voltage (Udc,r) 365 Feed-in start voltage (U_{dc start}) 80 V Input data Operating voltage range 65-530 65-530 MPP voltage range (at rated power) 260-480 260-480 MPPT2 MPPT1 MPPT2 MPPT1 Max. short circuit current per MPPT 41.25 36 41.25 36 Number of DC connections ² 2 2 2 MPPT1 MPPT2 Total MPPT1 MPPT2 Total 8,000 8,000 8,000 10,250 10,250 10,250 Max. usable DC power W Max. PV generator output Wpeak 11,520 11,520 11,520 13,500 13,000 15,000 208 V_{ac} 220 V_{ac} 208 V_{ac} 220 V_{ac} 240 V_{ac} 240 V_{ac} AC rated power (Pac,r) W 10,000 7,680 7,680 7,680 9,450 10,000 Apparent power VA 7,680 7,680 7,680 9,450 10,000 10,000 Output data VA 7,680 7,680 7,680 9,450 10,000 10,000 Max. Output power 32.0 Rated AC output current 36.9 34.9 45.45 45.45 41.7 Single phase 208 V / 220 V / 240 V (-12 / +10%) Mains connection (Uac,r) V Frequency 50 Hz / 60 Hz (45 Hz-66 Hz) Hz (frequency range fmin - fmax) Distortion factor % < 3.5 0.8-1 ind. / cap. Adjustable power factor Output data PV Point 120 V_{ac} 240 V_{ac} 220 Vac 240 Vac 120 V. 220 V_{ac} 1,560 Nom. Output power PV Point VA 2,860 3,120 1,560 2,860 3,120 Rated AC voltage PV Point Single phase 120 V / 220 V / 240 V < 23 Switching time

The Fronius GEN24 can be upgraded to a Fronius GEN24 Plus hybrid inverter in the future through the UP.storage software upgrade. This upgrade activates battery functionality, enabling the possibility of a Full Backup power solution. However, external grid switching devices are required for this functionality. The technical specifications for battery operation and Full Backup operation are detailed below:

Full Backup power and battery function only available with GEN24 Plus			Primo GEN24 208-240 Plus							
		7.	7	10.0						
data :kup ³			220 V _{ac}	240 V _{ac}	220 V _{ac}	240 V _{ac}				
Output data Full Backup	Rated Output power Full Backup	VA	7,680 7,680 10		10,000	10,000				
tpu I Ba	Mains connection Full Backup	٧	1~NPE 220 V / 240 V							
o II	Switching time	sec.		< 45						
_	Number of DC inputs			1						
tio T	Max. Input current (Idc max)	А	22							
tte	DC input voltage range (U _{dc min} - U _{dc max}) ⁴	V	150-455							
Battery connection	Connection technology DC battery		1x DC+ and 1x DC- spring-type terminals for solid: copper AWG 12-8							
8	Max. Charging power with AC coupling ⁵	W	7,68	00						

¹ The combined I_{sc} of each string, multiplied by a factor of 1.25, must be less than or equal to the ISC of the respective MPPT.

² The maximum usable input current of the 7.7kW and 10.0kW is 22A for MPPT1 and 22A for MPPT2.

³ For Full Backup, additional external components are required for grid separation.

⁴ AC power derating of the inverter occurs with a DC battery input voltage of 419.7 V and higher.

⁵ Depending on the connected battery.

10.0				Primo GEN24 208-240 & GEN24 208-240 Plus									
Weight (invertor) Use /kg				7.7 10.0									
Protection classe		Dimensions (height × width × depth)	inch/mm										
Protection class		Weight (inverter)	lbs./kg			45.97 lbs.	/ 20.85 kg						
Night consumption		Protection class				· · · · · · · · · · · · · · · · · · ·							
Overvottage category (DC/AC) * 2/4													
Cooling			W										
Installation													
Ambient temperature range							0						
Permissible humidity			%F./%C		Inc			on					
Noise emissions		·											
Connection technology AC	ata												
Connection technology AC	βp												
Connection technology AC	nera		10,111	2x DC+1, 2x DC+2 and 4x DC- spring-type terminals for solid: copper									
UL 1741 Third Edition (incl. UL1741 Supplement SA and SB), UL CRD - Non-Isolated EPS Interactive PV Inverters Rated Less Than 30kVA UL1998 (for Inventories: AFC, MUL) PVRSE and isolation monitoring), IEEE 1547:2018 incl. IEEE 1547:2020, IEEE 1547:2003 incl. IEEE 1547:2020, IEEE 1547:2005 ANSI/IEEE C82.41, FCC Part 15 A & B, CSA C22.2 No.370-23, CSA C22.3 No.9:20 UL16998:2021 Austria	Geı	Connection technology AC		Spring-type terminals for solid: copper stranded / fine stranded: copper: AWG 14-8									
Max. Efficiency		Certificates and standard compliance		UL CRD - Non-Isolated EPS Interactive PV Inverters Rated Less Than 30kVA UL1998 (for functions: AFCI, RCMU, PVRSE and isolation monitoring), IEEE 1547:2018 incl. IEEE 1547a:2020, IEEE 1547.1:2020, IEEE 1547:2003 incl. IEEE 1547.1:2005 ANSI/IEEE C62.41, FCC Part 15 A & B, CSA C22. 2 No. 107.1-16 (reaffirmed 2021), CSA C22.2 No.290-19, CSA C22.2 No.330-23, CSA C22.3 No.9:20									
Max. Efficiency % 97.2 97.2 97.5 97.2 97.5 97.2 97.5 Max. Efficiency		Country of manufacture	Austria										
Max. Efficiency % 97.2 97.2 97.5 97.2 97.5 97.2 97.5 Max. Efficiency													
MPP adjustment efficiency % > 99.9 DC insulation measurement Integrated DC disconnector Integrated Reverse polarity protection Arc Fault Circuit Interruption (Arc Guard) MLAN / 2 x Ethernet LAN Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON) 6 digital inputs Connection to ripple control receiver, energy management 6 digital inputs/outputs Integrated Emergency shutdown (WSD) Integrated Integrated Integrated	≿			208 V _{ac}	220 V _{ac}	240 V _{ac}	208 V _{ac}	220 V _{ac}	240 V _{ac}				
MPP adjustment efficiency % > 99.9 DC insulation measurement Integrated DC disconnector Integrated Reverse polarity protection Arc Fault Circuit Interruption (Arc Guard) MLAN / 2 x Ethernet LAN Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON) 6 digital inputs Connection to ripple control receiver, energy management 6 digital inputs/outputs Integrated Emergency shutdown (WSD) Integrated Integrated Integrated	ienc	Max. Efficiency	%	97.2	97.2	97.5	97.2	97.2	97.5				
MPP adjustment efficiency % > 99.9 DC insulation measurement Integrated DC disconnector Integrated Reverse polarity protection Arc Fault Circuit Interruption (Arc Guard) MLAN / 2 x Ethernet LAN Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON) 6 digital inputs Connection to ripple control receiver, energy management 6 digital inputs/outputs Integrated Emergency shutdown (WSD) Integrated Integrated Integrated	ffic	CEC (ηCEC)	%	96.5	96.5	97	96.5	96.5	97				
DC disconnector Reverse polarity protection Arc Fault Circuit Interruption (Arc Guard) MLAN / 2 x Ethernet LAN Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON) 6 digital inputs Connection to ripple control receiver, energy management 6 digital inputs/outputs Emergency shutdown (WSD) Integrated Integrated	Ú	MPP adjustment efficiency	%	> 99.9									
DC disconnector Reverse polarity protection Arc Fault Circuit Interruption (Arc Guard) MLAN / 2 x Ethernet LAN Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON) 6 digital inputs Connection to ripple control receiver, energy management 6 digital inputs/outputs Emergency shutdown (WSD) Integrated Integrated													
WLAN / 2 x Ethernet LAN Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON) 6 digital inputs Connection to ripple control receiver, energy management Integrated Emergency shutdown (WSD) Integrated	t e	DC insulation measurement				Integr	ated						
WLAN / 2 x Ethernet LAN Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON) 6 digital inputs Connection to ripple control receiver, energy management Integrated Emergency shutdown (WSD) Integrated	ctiv	DC disconnector		Integrated									
WLAN / 2 x Ethernet LAN Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON) 6 digital inputs Connection to ripple control receiver, energy management Integrated Emergency shutdown (WSD) Integrated	ote	Reverse polarity protection				Integr	ated						
6 digital inputs Connection to ripple control receiver, energy management Integrated Emergency shutdown (WSD) Integrated	P. eq	Arc Fault Circuit Interruption (Arc Guard)				Integr	ated						
6 digital inputs Connection to ripple control receiver, energy management Integrated Emergency shutdown (WSD) Integrated													
		WLAN / 2 x Ethernet LAN		Fronius Solar.web, Modbus TCP, Fronius Solar API (JSON)									
	ces	6 digital inputs		Connection to ripple control receiver, energy management									
	erfa	6 digital inputs/outputs		Integrated									
	Inte	Emergency shutdown (WSD)		Integrated									
Tronius Ginart Meter www / Moubus Kro (tiliru-party)		Data logger and web server		Fronius Smart Meter WR / Modbus RTU (third-party)									

Fronius Primo GEN24



to empower.

For more information about the product, visit:

www.fronius.us/gen24

Fronius USA LLC

Headquarters 6797 Fronius Drive Portage, IN 46368 USA pv-sales-usa@fronius.com www.fronius.us Fronius International GmbH

Froniusplatz 1 4600 Wels Austria pv-sales@fronius.com www.fronius.com